


AC8004

FRONT LOAD HIGH SECURITY BILL CHANGER

SLEEK STAINLESS STEEL DESIGN



Dual banknote
validators



High security,
stainless steel
design



Dual hoppers:
holds 11,200
coins total



Changing the IndustrySM



Multiple
upgrade
options



Various
currencies
accepted



Streamline
customer
traffic



Unparalleled
customer
service



American Changer

Fort Lauderdale, Florida 33309

T: (+1) 954-917-3009 F: (+1) 954-917-3079

www.americanchanger.com www.hoffmanmint.com



AC8004 Product Features		Description
2-Banknote Validators and Stackers *		Base unit is the Pyramid brand paper currency “banknote” validator. Can be programmed to accept many world currencies. Astro brand also used. Accepts \$1, \$5, \$10 and \$20. Stacker capacity is 2,200 notes
2-Coin Hoppers**		Holds up to 5,600 quarters/tokens per hopper (11,200 total) or 4,400 \$1 coins per hopper (8,800 total). Hopper dispenses 4 coins per second on average. Hopper capacity may be reduced using different coins or validators
2 -Locks & Keys		Medeco brand – high security hardened steel/special keys
1-Control Board/Power Supply/Electrical Configuration		Switchable input: 115/230 volt, 50/60 Hz. Various plug configurations. Power consumption: Board 10W max, Hopper 22W max, Validator 50W max
Ambient Temperature for Field of Use		32° to 130° Fahrenheit or 0° to 54° Celsius
Decal		As seen on front page. Customizable
Cabinet Construction		Cabinet is 11 gauge stainless steel Door is 11 gauge stainless steel
Cabinet Finish		Welded stainless steel cabinet. Available in powder coated galvaneal steel (lesser cost)
Dimensions***		25 W x 26 ³ / ₈ H x 13 ¹ / ₂ D inches 63.5 W x 67 H x 34.3 D centimeters
Weight***		162 Lbs. (about 73.5 Kg)
Options – Security	Part #	Description
Contact Alarm	AC1090	Alert sound to 130 dB
Tilt Alarm	AC1091	Alert sound to 130 dB
Options – Other	Part #	Description
MEI Brand 1000 Banknote Stacker*	AC1045.2	Stacker holds 1000 paper currency “banknotes”
Freeze Protection	AC1061 -HTR	Internal electric strip heater
Coin Catcher	AC2042	Receives and holds tokens for easy access by customers
Coin/ Quarter Acceptor	AC2066.4	Condor brand \$1 coin acceptor. Programmable to accept different coins and convert from large to small coinage
Electronic Coin Acceptor	AC2066.5	High security. IDX brand electronic coin acceptor
Audit Printer	AC7070.2	Prints out audit information
Iris System Upgrade	AC8001-IRIS	Ethernet or cellular credit card system
Stainless Steel Console Base	AC8470	Dimensions***: 25 W x 26 H x 13 ¹ / ₂ D inches 63.5 W x 66 H x 34.3 D centimeters
MEI Brand Validator and Stacker*	AC9003.2-500	Validates paper currency “banknotes”. \$1, \$5, \$10 and \$20. Stacker capacity is 500 notes
CoinCo Brand “Vantage” Validator and Stacker*	AC9031-400	Validates paper currency “banknotes”. Stacker capacity is 500 notes
CoinCo Brand 1100 Banknote Stacker*	AC9031-1000	Stacker holds 1100 paper currency “banknotes”
Warranty – Limited		12 months on entire machine, 24 months for validators. See American Changer’s Terms and Conditions of Sale for details

* Validator stacker capacity is based on the size of a USA banknote which in inches measures 6.14” L x .0043”H x 2.61”W or measured in millimeters 155.9 L x 0.10 H x 66.2 W. The weight of the banknote is 1 gram. American Changer is at sole discretion and may choose the brand of validators it uses.

** Hopper capacities are based on a coin/token the size of a 2014 USA quarter or a \$1 USA coin. The measurements of said coins/tokens are 0.955/1.043 inches or 1.75/26.5 millimeters and a weight of 0.182/0.260 Troy ounces (USA) or 5.670 /8.100 grams respectively. Hopper capacities may be increased or reduced using different sizes of coins/tokens.

*** Dimensions and weights are reasonably close estimates measured prior to packaging for shipment by American Changer. They only consider the base product features – no other options.

Other options can be considered in addition to those listed. All options and/or customized features are an additional price over the base price of the product. **No** products and/or services supplied by American Changer are 100% security proof and all of American Changer’s products and services are to be used by the owner’s best judgement. Capacities are approximations.

Installation, use and maintenance (service) must be done in accordance with the applicable manuals provided by American Changer with the products in this document and comply with any and all pertinent law or regulations. Specifications on this document can vary without notice.