

CRYPTOTAP PLUS WIRING GUIDE			
Timer Model	Hookup		Notes
	CryptoTap	Timer	
Dixmor Timers			
Dixmor LED7 & Dixmor DX2002	Red/Green	Pin 9	LED7 firmware 7.32 or greater required
	Red/Green & Black	Pin 6	
	Yellow	Pin 7	
Dixmor LED9	Red/Green	Pin 8	LED9 setting [CC Y]
	Red/Green & Black	Pin 6	
	Yellow	Pin 7	
Dixmor DX2000	Red/Green	Pin 5	Configuration Count Down Coin
	Red/Green & Black	Pin 10	
	Yellow	Pin 9	
Dixmor LED6 & Dixmor LED5	Red/Green	Pin 8	LED5 firmware 2.32 or greater required
	Red/Green & Black	Pin 9	
	Yellow	Pin 10	
Dixmor LED3	Red/Green	Pin 2	Configuration Count Down Coin
	Red/Green & Black	Pin 6	
	Yellow	Pin 7	
IDX Timers			
IDX GT200 & IDX LTT800/LTT802	Red/Green	Pin 3	
	Red/Green & Black	Pin 2	
	Yellow	Pin 1	

CRYPTOTAP PLUS WIRING GUIDE			
Timer Model	Hookup		Notes
	CryptoTap	Timer	
GinSan Timers			
GinSan GS-31/31B & GinSan GS-401/GS-402	Red/Green	Pin 4	
	Red/Green & Black	Pin 1	
	Yellow	Pin 3	
GinSan GS-400	Red/Green	Red/Green	
	Red/Green & Yellow	Red	
	Black	Purple	
GinSan GS-7/GS-8/GS-75/GS-85/GS-87/GS-255	Red/Green	Pin 4	
	Red/Green & Black	Pin 1	
	Yellow	Pin 3	
Miscellaneous			
Dilling Harris Touch Select I	Red/Green	Coin Input	
	Red/Green & Yellow	24VAC Hot	
	Black	24VAC Common	
D&S S200/201/203/204/224	Red/Green	Pin 2	
	Red/Green & Black	Pin 6	
	Yellow	Pin 7	
Timemaster TM-5J & Coleman 1034	Red/Green	Pin 2	
	Red/Green & Yellow	Pin 10	
	Black	Pin 9	

CRYPTOTAP PLUS WIRING GUIDE

Timer Model	Hookup		Notes
	CryptoTap	Timer	
Coin Acceptors			
IDX Sensortron MA-800/X-10/X-20	Red/Green & Red/Green	Red/Green & Red/Green	
	Yellow	Yellow	
	Black	Black	
MICROcoin	Red/Green & Red/Green	Blue & Blue	
	Yellow	Yellow	
	Black	Black	
Slug Buster I-III	Red/Green	Blue	If Purple wire is used - Red/Green to Purple, Red/Green & Yellow to Yellow, and Black to Black
	Red/Green & Black	Black	
	Yellow	Yellow	

CRYPTOTAP PLUS WIRING GUIDE

Timer Model	Hookup		Notes
	CryptoTap	Timer	
Vacuum Timers			
Infitec ASCR54	Red/Green	24 VAC Relay	24VAC Transformer and Relay Required
	Red/Green & Yellow	24 VAC Hot	
	Black	24 VAC Common	
SSAC	Red/Green	24 VAC Relay	24VAC Transformer and Relay Required
	Red/Green & Yellow	24 VAC Hot	
	Black	24 VAC Common	
IDX 411 120v	Red/Green & Red/Green	Pin 7 & Pin 8	24VAC transformer required (120VAC Hot - Pin 3 & 120VAC Common - Pin 1)
	Yellow	24 AC Hot	
	Black	24 AC common	
ParaPlate T24120	Red/Green & Red/Green	Coin Switch + & Coin Switch -	24VAC transformer required (120VAC Hot - Line Hot & 120VAC Common - Line Neutral)
	Yellow	24 AC Hot	
	Black	24 AC Common	
GinSan GS-403	Yellow	24 AC Hot	24VAC transformer required (120VAC Hot - Pin 1 & 120VAC Common - Pin 2)
	Black	24 AC Common	
	Red/Green	Pin 4 & Pin 5	