

WIRING INFORMATION – MA602-A / -C /-F

| <u>XEPTOR® CONNECTIONS TO DISPLAYS & TIMERS</u> | <u>XEPTOR® CONNECTIONS TO DISPLAYS & TIMERS</u> | <u>XEPTOR® CONNECTIONS TO DISPLAYS & TIMERS</u> | <u>XEPTOR® CONNECTIONS TO DISPLAYS & TIMERS</u> |
|---|---|---|---|
| LTT800 / LTT802 CONNECTIONS | D & S DISPLAY TIMER CONNECTIONS | IDX FLAT PACK 24 VAC CONNECTIONS | GINSAN 24 VOLT CONNECTIONS |
| MA602 LTT802 | MA602 202/203/204 | MA602 AT411/AT422 AT412 | MA602 GS-7/8/75 GS-87/255/402 |
| YELLOW PIN #1 | YELLOW BLK/YEL#7 | YELLOW PIN #2 | YELLOW #3 |
| BLACK PIN #2 | BLACK WHITE #6 | BLACK PIN #3 | BLACK #1 |
| RED/GREEN PIN #3 | RED/GREEN BLUE #2 | RED/GREEN PIN #7 | RED/GREEN #4 |
| RED/GREEN PIN #2 | RED/GREEN WHITE #6 | RED/GREEN PIN #8 or #3 | RED/GREEN #1 |
| BT800/BT802/BT902/BT912/ BT922-CONNECTIONS | GINSAN DISPLAY CONNECTIONS | IDX FLAT PACK 115/220 VAC CONNECTIONS | GINSAN GS9/403 115 VOLT CONNECTIONS |
| MA602 BT800-BT922 | MA602 GS31/GS31B | MA602 AT413 / AT414 | MA602 GS-9/403 |
| YELLOW PIN #1 | YELLOW RED | 115V/220 PIN #1 | YELLOW #7 |
| BLACK PIN #2 | BLACK PURPLE | COMMON PIN #3 | BLACK #5 |
| RED/GREEN PIN #3 | RED/GREEN RED/GRN | YELLOW PIN #2 | RED/GREEN #4 |
| RED/GREEN PIN #2 | RED/GREEN PURPLE | BLACK PIN #8 or #3 | RED/GREEN #5 |
| MONORAIL DISPLAY CONNECTIONS | SOUTHWEST- ELECTRONICS DISPLAY TIMER CONNECTIONS | RED/GREEN PIN #7 | |
| MA602 MDC | MA602 202/203/204 | RED/GREEN PIN #8 or #3 | GINSAN GS11 115 VOLT CONNECTIONS |
| YELLOW BLK-24V | YELLOW BLK/YEL#7 | | MA602 GS-11 |
| BLACK WH-COM | BLACK WHITE #6 | IDX PLUG IN TIMERS 24 VOLT CONNECTIONS | YELLOW #1 |
| RED/GREEN WH/GRN | RED/GREEN BLUE #2 | MA602 AT401/402/403 | BLACK #4 |
| RED/GREEN WH-COM | RED/GREEN WHITE #6 | YELLOW #2 | RED / GREEN #3 |
| DIXMOR LED 3 CONNECTIONS | SPECIALTY MFG CONNECTIONS | BLACK #1 | RED / GREEN #4 |
| MA602 LED 3 | MA602 TIME MACHINE | RED/GREEN #3 | |
| YELLOW #7 RED | YELLOW BLK-24V | RED/GREEN #1 | KELTNER CONNECTIONS |
| BLACK #6 GREEN | BLACK WHT-COM | RED/GREEN #3 | MA602 D9 |
| RED/GREEN #2 BROWN | RED/GREEN BLK-24V | RED/GREEN #1 | YELLOW #1 |
| RED/GREEN #1 GRAY/#6 GREEN | RED/GREEN YEL- COIN SWITCH | RED/GREEN #1 | BLACK #2 |
| DIXMOR DX2000 CONNECTIONS | MAGIKTIMER PLUS 24 VOLT CONNECTIONS | MONORAIL PLUG IN TIMER 24 VOLT CONNECTIONS | RED/GREEN #4 |
| MA602 DX2000 | MA602 24 VOLT CONNECTIONS | MA602 FOR G2 | RED/GREEN # 5 or #2 |
| YELLOW #9 | YELLOW #2 | YELLOW #2 | KELTNER CONNECTIONS |
| BLACK #10 | BLACK #3 | BLACK #1 | MA602 LC-1 |
| RED / GREEN #10 | RED/GREEN #6 | RED/GREEN #3 | X10 |
| RED / GREEN #5 | RED/GREEN # 7 or #3 | RED/GREEN #1 | YELLOW #2 |
| DIXMOR DX300 CONNECTIONS | D & S CONNECTIONS | MONORAIL TIMER 24 VOLT CONNECTIONS | BLACK #1 |
| MA602 DX300 | MA602 NON- DISPLAY | MA602 MDC | RED/GREEN #4 |
| YELLOW #7 | YELLOW 24V HOT (L1) | YELLOW BLK-24V | RED/GREEN # 3 or #1 |
| BLACK #6 | BLACK 24V COMMON (L2) | BLACK WH-COM | |
| RED/GREEN #6 | RED/GRN COIN | RED/GREEN WH/GRN | PARKER CONNECTIONS |
| RED/GREEN #1 | RED/GRN 24V COMMON (L2) | RED/GREEN WH-COM | MA602 24 VOLT CONNECTIONS |
| TIME MASTER TM5/TM5J/LED5/CT2000 CONNECTIONS | MAGIC WAND & JIM COLMEN TM5/TM5J/ CT2000 CONNECTIONS | PARAPLATE CONNECTIONS | MA602 T24120 |
| MA602 TIME MASTER | MA602 TIME MASTER | MA602 T24200 | YELLOW #3 |
| YELLOW #9 ORANGE | YELLOW #9 ORANGE | YELLOW #2 | BLACK #1 |
| BLACK #10 GREEN | BLACK #10 GREEN | BLACK #3 | RED/GREEN #4 |
| RED/GREEN #10 GREEN | RED/GREEN #10 GREEN | RED/GREEN #7 | RED/GREEN #1 |
| RED/GREEN #2 ORANGE/BLK | RED/GREEN #2 ORANGE/BLK | RED/GREEN #8 or #3 | |
| | | PARAPLATE -NEW 24VAC CONNECTIONS | MARK VII CONNECTIONS |
| | | MA602 T24200 | MA602 ACCUTIME |
| | | YELLOW #1 | YELLOW #2 |
| | | BLACK #2 | BLACK #1 |
| | | RED/GREEN #5 | RED/GREEN #4 |
| | | RED/GREEN #6 or #2 | RED/GREEN #1 |