

WIRING INFORMATION – MA800-MA812-X10

FOR MA803 AND X10DM CHECK WITH FACTORY

| <u>XEPTOR® CONNECTIONS TO DISPLAYS & TIMERS</u> | <u>XEPTOR® CONNECTIONS TO DISPLAYS & TIMERS</u> | <u>XEPTOR® CONNECTIONS TO DISPLAYS & TIMERS</u> | <u>XEPTOR® CONNECTIONS TO DISPLAYS & TIMERS</u> |
|---|--|---|--|
| <p style="text-align: center;">LTT800 / LTT802 CONNECTIONS</p> <p>MA800 or LTT802 X10</p> <p>YELLOW PIN #1 BLACK PIN #2 RED/GREEN PIN #3 RED/GREEN PIN #2</p> <p style="text-align: center;">BT800/BT802/BT902/BT912/ BT922-CONNECTIONS</p> <p>MA800 or BT800-BT922 X10</p> <p>YELLOW PIN #1 BLACK PIN #2 RED/GREEN PIN #3 RED/GREEN PIN #2</p> <p style="text-align: center;">MONORAIL DISPLAY CONNECTIONS</p> <p>MA800 or MDC X10</p> <p>YELLOW BLK-24V BLACK WH-COM RED/GREEN WH/GRN RED/GREEN WH-COM</p> <p style="text-align: center;">DIXMOR LED 3 CONNECTIONS</p> <p>MA800 or LED 3 X10</p> <p>YELLOW #7 RED BLACK #6 GREEN RED/GREEN #2 BROWN RED/GREEN #1 GRAY/#6 GREEN</p> <p style="text-align: center;">DIXMOR DX2000 CONNECTIONS</p> <p>MA800 or DX2000 X10</p> <p>YELLOW #9 BLACK #10 RED/GREEN #10 RED/GREEN #5</p> <p style="text-align: center;">DIXMOR DX300 CONNECTIONS</p> <p>MA800 or DX300 X10</p> <p>YELLOW #7 BLACK #6 RED/GREEN #6 RED/GREEN #1</p> <p style="text-align: center;">TIME MASTER TM5/TM5J/LED5/CT2000 CONNECTIONS</p> <p>MA800 or TIME MASTER X10</p> <p>YELLOW #9 ORANGE BLACK #10 GREEN RED/GREEN #10 GREEN RED/GREEN #2 ORANGE/BLK</p> | <p style="text-align: center;">D & S DISPLAY TIMER CONNECTIONS</p> <p>MA800 or 202/203/204 X10</p> <p>YELLOW BLK/YEL#7 BLACK WHITE #6 RED/GREEN BLUE #2 RED/GREEN WHITE #6</p> <p style="text-align: center;">GINSAN DISPLAY CONNECTIONS</p> <p>MA800 or GS31/GS31B X10</p> <p>YELLOW RED BLACK PURPLE RED/GREEN RED/GRN RED/GREEN PURPLE CALL FOR TIMER CONNECTIONS</p> <p style="text-align: center;">DILLING & HARRIS CONNECTIONS</p> <p>MA800 or TIME MACHINE X10</p> <p>YELLOW BLK-24V BLACK WHT-COM RED/GREEN BLK-24V RED/GREEN YEL- COIN SWITCH</p> <p style="text-align: center;">SPECIALTY MFG CONNECTIONS</p> <p>MA800 or TIME MACHINE X10</p> <p>YELLOW BLK-24V BLACK WHT-COM RED/GREEN BLK-24V RED/GREEN YEL- COIN SWITCH</p> <p style="text-align: center;">SECURECOIN TIMER 24 VOLT CONNECTIONS</p> <p>MA800 or #ET X10 SAME AS IDX AT411</p> <p>YELLOW #2 BLACK #3 RED/GREEN #7 RED/GREEN # 8 or #3</p> <p style="text-align: center;">D & S CONNECTIONS</p> <p>MA800 or NON- DISPLAY X10</p> <p>YELLOW 24V HOT (L1) BLACK 24V COMMON (L2) RED/GRN COIN RED/GRN 24V COMMON (L2)</p> <p style="text-align: center;">MAGIC WAND & JIM COLMEN TM5/TM5J/ CT2000 CONNECTIONS</p> <p>MA800 or TIME MASTER X10</p> <p>YELLOW #9 ORANGE BLACK #10 GREEN RED/GREEN #10 GREEN RED/GREEN #2 ORANGE/BLK</p> | <p style="text-align: center;">IDX FLAT PACK 24 VAC CONNECTIONS</p> <p>MA800 or AT411/AT422 X10 AT412</p> <p>YELLOW PIN #2 BLACK PIN #3 RED/GREEN PIN #7 RED/GREEN PIN #8 or #3</p> <p style="text-align: center;">IDX FLAT PACK 115 VAC CONNECTIONS</p> <p>MA800 or AT413 X10</p> <p>115V HOT PIN #1 115V COMMON PIN #3 YELLOW PIN #2 BLACK PIN #8 or #3 RED/GREEN PIN #7 RED/GREEN PIN #8 or #3</p> <p style="text-align: center;">IDX PLUG IN TIMERS 24 VOLT CONNECTIONS</p> <p>MA800 or AT401/402/403 X10</p> <p>YELLOW #2 BLACK #1 RED/GREEN #3 RED/GREEN #1</p> <p style="text-align: center;">MONORAIL PLUG IN TIMER 24 VOLT CONNECTIONS</p> <p>MA800 or FOR G2 X10</p> <p>YELLOW #2 BLACK #1 RED/GREEN #3 RED/GREEN #1</p> <p style="text-align: center;">MONORAIL TIMER 24 VOLT CONNECTIONS</p> <p>MA800 or MDC X10</p> <p>YELLOW BLK-24V BLACK WH-COM RED/GREEN WH/GRN RED/GREEN WH-COM</p> <p style="text-align: center;">PARAPLATE CONNECTIONS</p> <p>MA800 or T24120 X10</p> <p>YELLOW #2 BLACK #3 RED/GREEN #7 RED/GREEN #8 or #3</p> <p style="text-align: center;">PARAPLATE -NEW 24VAC CONNECTIONS</p> <p>MA800 or T24200 X10</p> <p>YELLOW #1 BLACK #2 RED/GREEN #5 RED/GREEN #6 or #2</p> | <p style="text-align: center;">GINSAN 24 VOLT CONNECTIONS</p> <p>MA800 or GS-7/8/75 X10 GS-87/255</p> <p>YELLOW #3 BLACK #1 RED/GREEN #4 RED/GREEN #1 TOKEN INPUT #5 (GS87)</p> <p style="text-align: center;">GINSAN GS9 115 VOLT CONNECTIONS</p> <p>MA800 or GS-9 X10</p> <p>YELLOW #7 BLACK #5 RED/GREEN #4 RED/GREEN #5</p> <p style="text-align: center;">GINSAN GS11 115 VOLT CONNECTIONS</p> <p>MA800 or GS-11 X10</p> <p>YELLOW #1 BLACK #4 RED/GREEN #3 RED/GREEN #4</p> <p style="text-align: center;">KELTNER CONNECTIONS</p> <p>MA800 or D9 X10</p> <p>YELLOW #1 BLACK #2 RED/GREEN #4 RED/GREEN # 5 or #2</p> <p style="text-align: center;">KELTNER CONNECTIONS</p> <p>MA800 or LC-1 X10</p> <p>YELLOW #2 BLACK #1 RED/GREEN #4 RED/GREEN # 3 or #1</p> <p style="text-align: center;">PARKER CONNECTIONS</p> <p>MA800 or X10</p> <p>YELLOW #3 BLACK #1 RED/GREEN #4 RED/GREEN #1</p> <p style="text-align: center;">MARK VII CONNECTIONS</p> <p>MA800 or ACCUTIME X10</p> <p>YELLOW #2 BLACK #1 RED/GREEN #4 RED/GREEN #1</p> |